



## **QolorPIX®**

QolorPIX Tape Controller is an innovative approach to pixel control which offers a high level of creativity combined with plug and play usability.

Each QolorPIX Tape Controller is pre-configured with personality profiles, which can be combined and tuned to produce thousands of dynamic effects using only a few DMX channels. Chases, fades, scrolls, bursts, and other effects can be created and saved as needed.

QolorPIX Pixel Controlled LED Tape connects to the **QolorPIX Tape Controller** using industry standard four pin XLR connectors. Within one minute, the QolorPIX system can be up and running.



The QolorPIX Tape Controller offers eight ports, each accommodating five meters of tape. It features an integrated power supply, a test function, and flicker finder for easy troubleshooting. It also offers wireless DMX control using City Theatrical's state of the art Multiverse® wireless DMX technology.

## **QolorPIX® Tape Controller** P/N 5850

## SPECIFICATIONS:

| Physical               |  |             |
|------------------------|--|-------------|
| Length                 | 34.6cm   | (13.6 in)   |
| Width                  | 20.3cm   | (8.0 in)    |
| Height                 | 8.9cm  | (3.5 in)    |
| Weight                 | 2.61kg   | (5.75 lbs.) |
| Construction           | NEMA 1 IP 20 Steel<br>Enclosure                            |             |
| Number of Outputs      | 8  |             |
| Output Connectors      | 4-Pin XLRF   |             |
| Input Power Connection | PowerCON   |             |
| DMX Connections        | 5-Pin XLR; Built-in<br>Multiverse wireless DMX<br>receiver |             |

| Electrical                     |            |          |
|--------------------------------|------------|----------|
| Max Pixels per Output          | 320        |          |
| Voltage                        | 85-264 VAC |          |
| Max Cable Distance to LED Tape | 10m        | (32.8ft) |
| Total Output (Watts)           | 600W       |          |

| Product Information |                    |  |
|---------------------|--------------------|--|
| Use Environment     | Indoor             |  |
| Compliance          | ETL, CE, RoHS, FCC |  |
|                     | A CC TO            |  |











The QolorPIX Tape Controller has a user-friendly control interface that allows the user to change mode, pixel length, dimmer, personality start address, and direction.